

X35

4 Channel DJ mixer



Overview

The X 35 is a high quality professional 4 channel DJ mixer from Studioma Professional.

Key Features

- Built-in USB MP3 media player with wireless Bluetooth connectivity.



Media Player
USB MP3 & BLUETOOTH



Bluetooth

- Built-in Bluetooth wireless streaming from smartphones, tablets and laptops.



Bluetooth

All Features



- High Quality 4 channel DJ mixer with Phono preamps.
- 3-band kill EQ (-30 dB) and gain control per channel.
- Balanced XLR mic input with gain and 2-band EQ.
- Built-in USB MP3 media player with wireless Bluetooth connectivity.
- Crossfader reverse / normal / flat / steep curve switch.
- Headphone cue Mix with blend switch.
- Separate master, record and booth RCA output.
- 1/4" headphone output with level control.
- Balanced XLR master output.
- Ultra smooth and sturdy faders.

Technical Specifications

Parameter	Specifications
Gain (Mic / Phono / Line)	40dB / 40dB / 0dB
Input Level Sensitivity (Mic / Phono / Line)	-40dBu / -40dBu / 0dBu
Main Output Levels (Nominal / Max)	0dBu (0.775V) / +18dBu (6.15V RMS)
Booth Output Levels	0dBu (0.775V) Nominal /
(Nominal / Max)	+18dBu (6.15V RMS) Max
Frequency Response	20Hz-22kHz (+/-3dB)
Total Harmonic Distortion	0.07% @ 1kHz 0.1% @ 1kHz
Equalisation Line Input	+10/-12dB @ 10kHz / +12/-24dB @
(Treble / Mid / Bass)	1.3kHz / +12/-29dB @ 50Hz
Signal to Noise Ratio (Mic / Line)	60dB / 82dB
Dimensions (W x D x H) mm	242 x 104 x 294
Net Weight (Kg)	2.4

Support

For sales, support, pricing and availability:
Email: info@audioplus-india.com
Telephone: 022-42869000 / 001
WhatsApp: +91-8879028079
(Monday to Saturday between 10:00 a.m to 6:00 p.m.)
Contact Us:
<http://www.studiomasterprofessional.com/home/contact>



Scan QR Code for More Details



Scan QR Code to Watch Video

For after-sales service and support: Email: sales.support@audioplus-india.com Telephone: 022-42869010 / 49 / 57

Subscribe to our Channel

Studiomaster[®]
PROFESSIONAL

On

 YouTube



bit.ly/SMPYT-S



Studiomaster Professional



* Product design and specifications are subject to change without notice.

Studiomaster Professional is a registered trademark of Audioplus in India. © Copyright Audioplus, 2008. All rights reserved. Any unauthorised reproduction or use of logos, images or design elements is strictly prohibited by law. No part of the compilation may be reproduced in any manner or translated without written permission.

Code: Rev000 / SMP X35 Datasheet / Jan 2022

Brought to you by:

AUDIOPLUS

A1/A2, Giriraj Indl. Est., Mahakali Caves Road, Andheri (E), Mumbai - 400 093, India Tel.: +91-22-4286 9000/ 001 W: www.audioplus-india.com